

# PRODUCT DATA SHEET

## Phase Rotation Indicators

Checks phase sequence and phase status

### Features:

**100-660 VAC rated test range** for testing phase orientation of three phase power sources over 50-70 Hz frequency range. Five LEDs: two of which indicate phase orientation (clockwise or counter-clockwise); and whether each of three phases is live. Operation is simple.

**Complete with** three large alligator clips. Weight 5oz. (140g)  
Dimensions: 3.5x2x1" (90x50x25mm).

### Motor Rotation & 3-Phase Tester

Combines above 3-phase rotation tester with a motor rotation tester for measuring the rotation direction of motor shafts. Ensures motor is not damaged from incorrect wiring. Dimensions: 5.9x3.3x1.5" (150x84x38mm). Weight 10oz. (283g). Complete with three large alligator clips.



### Ordering Information

**480300**.....Phase Rotation Tester  
**480303**.....Motor Rotation & 3-Phase Tester

### Accessories

**409996**.....Vinyl Pouch Carrying Case

**EXTECH**  
INSTRUMENTS

ISO 9001 Certified

Available at:

[www.Electrical-Contractor.net](http://www.Electrical-Contractor.net)  
[www.Contractors-Books.com](http://www.Contractors-Books.com)