

# MiniTec™ Manual Ranging Digital MultiMeter

Rugged pocket design, 8 functions

## Features:

- Large 2000 count LCD display
- Measures AC/DC Voltage, AC/DC Current and Resistance
- 1.5V and 9V Battery tests under load
- Continuity beeper, Diode test
- 10A fuse protection
- Overload protection and indication
- Includes protective rubber holster, 9V battery and test leads



**CAT II - 600V**

Specifications	Ranges	Max Resolution	Basic Accuracy (%rdg+digits)
DC Voltage:	200mV, 2000mV, 20V, 200V, 600V	0.1mV	±(0.5% + 2d)
AC Voltage:	200V, 600V	0.1V	±(1.5% + 5d)
DC Current:	200mA, 10A	0.1mA	±(1.2% + 2d)
AC Current:	200mA, 10A	0.1mA	±(1.8% + 5d)
Resistance (Ω):	200, 2000, 20k, 200k, 2000k	0.1Ω	±(0.8% + 2d)
Continuity:	<30 ohms		
Diode Test:	yes		
Battery Test:	9V	10mV	±(1.0% + 2d)
	1.5V	10mV	±(1.0% + 2d)
Power:	one 9V battery		
Dimensions:	4.8 x 2.4 x 1.6" (122 x 61 x 40mm)		
Weight:	9.17oz (260g)		

## Ordering Information:

- MN25** .....Manual Ranging MiniTec™  
**MN25-NIST** .....Manual Ranging MiniTec™ with NIST Certificate  
**409992** .....Vinyl pouch carrying case

Available at:

[www.Electrical-Contractor.net](http://www.Electrical-Contractor.net)  
[www.Contractor-Books.com](http://www.Contractor-Books.com)

ISO 9001:2000 CERTIFIED

**Make mine an Extech!**



09/24/04 - R1